

PACKAGED FIRE PUMP SYSTEM

DIMENSIONS FOR DRAWING EFPS1

Section 918 Page 201

Date AUGUST 2000

| PUMP MODEL | GPM | SYSTEM SUCTION DIAMETER | SYSTEM DISCHARGE DIAMETER | SYSTEM LENGTH | SYSTEM WIDTH |
|------------|------|-------------------------|---------------------------|---------------|--------------------|
| 4-481-11C | 750 | 6 (152) | 6 (152) | 79 (2007) | HB + 16 (HB + 406) |
| 4-481-11A | 750 | 6 (152) | 6 (152) | 79 (2007) | HB + 16 (HB + 406) |
| 4-481-15 | 750 | 6 (152) | 6 (152) | 82 (2083) | HB + 16 (HB + 406) |
| 5-481-15 | 750 | 6 (152) | 6 (152) | 82 (2083) | HB + 16 (HB + 406) |
| 4-491-11A | 750 | 6 (152) | 6 (152) | 79 (2007) | HB + 16 (HB + 406) |
| 4-491-11C | 750 | 6 (152) | 6 (152) | 79 (2007) | HB + 16 (HB + 406) |
| 4-491-14C | 750 | 6 (152) | 6 (152) | 82 (2083) | HB + 16 (HB + 406) |
| 5-491-18A | 750 | 6 (152) | 6 (152) | 91 (2311) | HB + 16 (HB + 406) |
| 6-491-12A | 750 | 6 (152) | 6 (152) | 79 (2007) | HB + 16 (HB + 406) |
| 4-492-18 | 750 | 6 (152) | 6 (152) | 83 (2108) | HB + 16 (HB + 406) |
| 5-481-11B | 1000 | 8 (203) | 6 (152) | 82 (2083) | HB + 16 (HB + 406) |
| 5-481-11C | 1000 | 8 (203) | 6 (152) | 82 (2083) | HB + 16 (HB + 406) |
| 5-481-15 | 1000 | 8 (203) | 6 (152) | 86 (2184) | HB + 16 (HB + 406) |
| 5-481-17 | 1000 | 8 (203) | 6 (152) | 87 (2210) | HB + 16 (HB + 406) |
| 6-481-11 | 1000 | 8 (203) | 6 (152) | 72 (1829) | HB + 16 (HB + 406) |
| 5-491-18A | 1000 | 8 (203) | 6 (152) | 89 (2261) | HB + 16 (HB + 406) |
| 5-492-18 | 1000 | 8 (203) | 6 (152) | 86 (2184) | HB + 16 (HB + 406) |
| 6-481-20 | 1250 | 8 (203) | 8 (203) | 90 (2286) | HB + 16 (HB + 406) |
| 6-481-15 | 1250 | 8 (203) | 8 (203) | 87 (2210) | HB + 16 (HB + 406) |
| 6-481-18B | 1250 | 8 (203) | 8 (203) | 90 (2286) | HB + 16 (HB + 406) |
| 8-481-12 | 1250 | 10 (254) | 8 (203) | 81 (2057) | HB + 16 (HB + 406) |
| 8-481-21 | 1250 | 10 (254) | 8 (203) | 85 (2159) | HB + 16 (HB + 406) |
| 5-491-14A | 1250 | 8 (203) | 8 (203) | 89 (2261) | HB + 16 (HB + 406) |
| 5-491-18A | 1250 | 8 (203) | 8 (203) | 92 (2337) | HB + 16 (HB + 406) |
| 6-481-20 | 1500 | 8 (203) | 8 (203) | 90 (2286) | HB + 16 (HB + 406) |
| 6-481-15 | 1500 | 8 (203) | 8 (203) | 87 (2210) | HB + 16 (HB + 406) |
| 6-481-18B | 1500 | 8 (203) | 8 (203) | 90 (2286) | HB + 16 (HB + 406) |
| 8-481-12 | 1500 | 10 (254) | 8 (203) | 81 (2057) | HB + 16 (HB + 406) |
| 8-481-21 | 1500 | 10 (254) | 8 (203) | 85 (2159) | HB + 16 (HB + 406) |
| 6-492-10 | 1500 | 10 (254) | 8 (203) | 87 (2210) | HB + 16 (HB + 406) |
| 8-481-21 | 2000 | 10 (254) | 10 (254) | 99 (2515) | HB + 16 (HB + 406) |
| 6-481-15B | 2000 | 10 (254) | 10 (254) | 97 (2464) | HB + 16 (HB + 406) |
| 6-481-18C | 2000 | 10 (254) | 10 (254) | 100 (2540) | HB + 16 (HB + 406) |
| 6-481-20 | 2000 | 10 (254) | 10 (254) | 100 (2540) | HB + 16 (HB + 406) |
| 8-481-17B | 2000 | 10 (254) | 10 (254) | 95 (2413) | HB + 16 (HB + 406) |
| 6-491-19A | 2000 | 10 (254) | 10 (254) | 100 (2540) | HB + 16 (HB + 406) |
| 8-492-15 | 2000 | 10 (254) | 10 (254) | 94 (2388) | HB + 16 (HB + 406) |
| 8-481-21A | 2500 | 10 (254) | 10 (254) | 101 (2565) | HB + 16 (HB + 406) |
| 8-481-17B | 2500 | 10 (254) | 10 (254) | 97 (2464) | HB + 16 (HB + 406) |
| 8-491-14A | 2500 | 10 (254) | 10 (254) | 106 (2692) | HB + 16 (HB + 406) |
| 8-491-18A | 2500 | 10 (254) | 10 (254) | 106 (2692) | HB + 16 (HB + 406) |
| 10-481-18 | 3000 | 12 (305) | 12 (305) | 107 (2718) | HB + 18 (HB + 457) |
| 8-491-14A | 3000 | 12 (305) | 12 (305) | 102 (2591) | HB + 18 (HB + 457) |
| 8-491-18A | 3000 | 12 (305) | 12 (305) | 102 (2591) | HB + 18 (HB + 457) |
| 10-492-18 | 3000 | 12 (305) | 12 (305) | 106 (2692) | HB + 18 (HB + 457) |
| 10-481-18 | 3500 | 12 (305) | 12 (305) | 107 (2718) | HB + 18 (HB + 457) |
| 10-492-18 | 3500 | 12 (305) | 12 (305) | 106 (2692) | HB + 18 (HB + 457) |
| 10-481-18 | 4000 | 14 (356) | 12 (305) | 118 (2997) | HB + 18 (HB + 457) |
| 10-491-20 | 4000 | 14 (356) | 12 (305) | 126 (3200) | HB + 18 (HB + 457) |
| 10-491-20 | 4500 | 16 (406) | 14 (356) | 116 (2946) | HB + 18 (HB + 457) |
| 10-491-20 | 5000 | 16 (406) | 14 (356) | 116 (2946) | HB + 18 (HB + 457) |

NOTES

1. Refer to Section 912 & 913 for "HB" dimensions of required pump/driver combination.
2. All System dimensions are in inches (mm) and may vary ± 6 inches (152).
3. Dimensions for reference only. Refer to factory for job specific drawings.

■ PACKAGED FIRE PUMP SYSTEM
DIMENSIONS FOR DRAWING EFPS2

| PUMP MODEL | GPM | SYSTEM SUCTION DIAMETER | SYSTEM DISCHARGE DIAMETER | SYSTEM LENGTH | SYSTEM WIDTH |
|------------|------|-------------------------|---------------------------|---------------|--------------------|
| 4-481-11C | 750 | 6 (152) | 6 (152) | 89 (2261) | HB + 16 (HB + 406) |
| 4-481-11A | 750 | 6 (152) | 6 (152) | 89 (2261) | HB + 16 (HB + 406) |
| 4-481-15 | 750 | 6 (152) | 6 (152) | 92 (2337) | HB + 16 (HB + 406) |
| 5-481-15 | 750 | 6 (152) | 6 (152) | 92 (2337) | HB + 16 (HB + 406) |
| 4-491-11A | 750 | 6 (152) | 6 (152) | 89 (2261) | HB + 16 (HB + 406) |
| 4-491-11C | 750 | 6 (152) | 6 (152) | 89 (2261) | HB + 16 (HB + 406) |
| 4-491-14C | 750 | 6 (152) | 6 (152) | 92 (2337) | HB + 16 (HB + 406) |
| 5-491-18A | 750 | 6 (152) | 6 (152) | 101 (2565) | HB + 16 (HB + 406) |
| 6-491-12A | 750 | 6 (152) | 6 (152) | 89 (2261) | HB + 16 (HB + 406) |
| 4-492-18 | 750 | 6 (152) | 6 (152) | 93 (2362) | HB + 16 (HB + 406) |
| 5-481-11B | 1000 | 8 (203) | 6 (152) | 92 (2337) | HB + 16 (HB + 406) |
| 5-481-11C | 1000 | 8 (203) | 6 (152) | 92 (2337) | HB + 16 (HB + 406) |
| 5-481-15 | 1000 | 8 (203) | 6 (152) | 96 (2438) | HB + 16 (HB + 406) |
| 5-481-17 | 1000 | 8 (203) | 6 (152) | 97 (2464) | HB + 16 (HB + 406) |
| 6-481-11 | 1000 | 8 (203) | 6 (152) | 82 (2083) | HB + 16 (HB + 406) |
| 5-491-18A | 1000 | 8 (203) | 6 (152) | 99 (2515) | HB + 16 (HB + 406) |
| 5-492-18 | 1000 | 8 (203) | 6 (152) | 96 (2438) | HB + 16 (HB + 406) |
| 6-481-20 | 1250 | 8 (203) | 8 (203) | 104 (2642) | HB + 16 (HB + 406) |
| 6-481-15 | 1250 | 8 (203) | 8 (203) | 101 (2565) | HB + 16 (HB + 406) |
| 6-481-18B | 1250 | 8 (203) | 8 (203) | 104 (2642) | HB + 16 (HB + 406) |
| 8-481-12 | 1250 | 10 (254) | 8 (203) | 95 (2413) | HB + 16 (HB + 406) |
| 8-481-21 | 1250 | 10 (254) | 8 (203) | 100 (2540) | HB + 16 (HB + 406) |
| 5-491-14A | 1250 | 8 (203) | 8 (203) | 101 (2565) | HB + 16 (HB + 406) |
| 5-491-18A | 1250 | 8 (203) | 8 (203) | 104 (2642) | HB + 16 (HB + 406) |
| 6-481-20 | 1500 | 8 (203) | 8 (203) | 104 (2642) | HB + 16 (HB + 406) |
| 6-481-15 | 1500 | 8 (203) | 8 (203) | 101 (2565) | HB + 16 (HB + 406) |
| 6-481-18B | 1500 | 8 (203) | 8 (203) | 104 (2642) | HB + 16 (HB + 406) |
| 8-481-12 | 1500 | 10 (254) | 8 (203) | 95 (2413) | HB + 16 (HB + 406) |
| 8-481-21 | 1500 | 10 (254) | 8 (203) | 99 (2515) | HB + 16 (HB + 406) |
| 6-492-10 | 1500 | 10 (254) | 8 (203) | 99 (2515) | HB + 16 (HB + 406) |
| 8-481-21 | 2000 | 10 (254) | 10 (254) | 117 (2972) | HB + 16 (HB + 406) |
| 6-481-15B | 2000 | 10 (254) | 10 (254) | 115 (2921) | HB + 16 (HB + 406) |
| 6-481-18C | 2000 | 10 (254) | 10 (254) | 118 (2997) | HB + 16 (HB + 406) |
| 6-481-20 | 2000 | 10 (254) | 10 (254) | 118 (2997) | HB + 16 (HB + 406) |
| 8-481-17B | 2000 | 10 (254) | 10 (254) | 113 (2870) | HB + 16 (HB + 406) |
| 6-491-19A | 2000 | 10 (254) | 10 (254) | 118 (2997) | HB + 16 (HB + 406) |
| 8-492-15 | 2000 | 10 (254) | 10 (254) | 110 (2794) | HB + 16 (HB + 406) |
| 8-481-21A | 2500 | 10 (254) | 10 (254) | 117 (2972) | HB + 16 (HB + 406) |
| 8-481-17B | 2500 | 10 (254) | 10 (254) | 113 (2870) | HB + 16 (HB + 406) |
| 8-491-14A | 2500 | 10 (254) | 10 (254) | 124 (3150) | HB + 16 (HB + 406) |
| 8-491-18A | 2500 | 10 (254) | 10 (254) | 124 (3150) | HB + 16 (HB + 406) |
| 10-481-18 | 3000 | 12 (305) | 12 (305) | 125 (3175) | HB + 18 (HB + 457) |
| 8-491-14A | 3000 | 12 (305) | 12 (305) | 122 (3099) | HB + 18 (HB + 457) |
| 8-491-18A | 3000 | 12 (305) | 12 (305) | 122 (3099) | HB + 18 (HB + 457) |
| 10-492-18 | 3000 | 12 (305) | 12 (305) | 125 (3175) | HB + 18 (HB + 457) |
| 10-481-18 | 3500 | 12 (305) | 12 (305) | 125 (3175) | HB + 18 (HB + 457) |
| 10-492-18 | 3500 | 12 (305) | 12 (305) | 125 (3175) | HB + 18 (HB + 457) |
| 10-481-18 | 4000 | 14 (356) | 12 (305) | 136 (3454) | HB + 18 (HB + 457) |
| 10-491-20 | 4000 | 14 (356) | 12 (305) | 146 (3708) | HB + 18 (HB + 457) |
| 10-491-20 | 4500 | 16 (406) | 14 (356) | 140 (3556) | HB + 18 (HB + 457) |
| 10-491-20 | 5000 | 16 (406) | 14 (356) | 140 (3556) | HB + 18 (HB + 457) |

NOTES

1. Refer to Section 912 & 913 for "HB" dimensions of required pump/driver combination.
2. All System dimensions are in inches (mm) and may vary ±6 inches (152).
3. Dimensions for reference only. Refer to factory job specific drawings.

PACKAGED FIRE PUMP SYSTEM

DIMENSIONS FOR DRAWING EFPS3

Section 918 Page 203

Date AUGUST 2000

| PUMP MODEL | GPM | SYSTEM SUCTION DIAMETER | SYSTEM DISCHARGE DIAMETER | SYSTEM LENGTH | SYSTEM WIDTH |
|------------|------|-------------------------|---------------------------|---------------|--------------------|
| 4-481-11C | 750 | 6 (152) | 6 (152) | 89 (2261) | HB + 16 (HB + 406) |
| 4-481-11A | 750 | 6 (152) | 6 (152) | 89 (2261) | HB + 16 (HB + 406) |
| 4-481-15 | 750 | 6 (152) | 6 (152) | 92 (2337) | HB + 16 (HB + 406) |
| 5-481-15 | 750 | 6 (152) | 6 (152) | 92 (2337) | HB + 16 (HB + 406) |
| 4-491-11A | 750 | 6 (152) | 6 (152) | 89 (2261) | HB + 16 (HB + 406) |
| 4-491-11C | 750 | 6 (152) | 6 (152) | 89 (2261) | HB + 16 (HB + 406) |
| 4-491-14C | 750 | 6 (152) | 6 (152) | 92 (2337) | HB + 16 (HB + 406) |
| 5-491-18A | 750 | 6 (152) | 6 (152) | 101 (2565) | HB + 16 (HB + 406) |
| 6-491-12A | 750 | 6 (152) | 6 (152) | 89 (2261) | HB + 16 (HB + 406) |
| 4-492-18 | 750 | 6 (152) | 6 (152) | 93 (2362) | HB + 16 (HB + 406) |
| 5-481-11B | 1000 | 8 (203) | 6 (152) | 92 (2337) | HB + 16 (HB + 406) |
| 5-481-11C | 1000 | 8 (203) | 6 (152) | 92 (2337) | HB + 16 (HB + 406) |
| 5-481-15 | 1000 | 8 (203) | 6 (152) | 96 (2438) | HB + 16 (HB + 406) |
| 5-481-17 | 1000 | 8 (203) | 6 (152) | 97 (2464) | HB + 16 (HB + 406) |
| 6-481-11 | 1000 | 8 (203) | 6 (152) | 82 (2083) | HB + 16 (HB + 406) |
| 5-491-18A | 1000 | 8 (203) | 6 (152) | 99 (2515) | HB + 16 (HB + 406) |
| 5-492-18 | 1000 | 8 (203) | 6 (152) | 96 (2438) | HB + 16 (HB + 406) |
| 6-481-20 | 1250 | 8 (203) | 8 (203) | 104 (2642) | HB + 16 (HB + 406) |
| 6-481-15 | 1250 | 8 (203) | 8 (203) | 101 (2565) | HB + 16 (HB + 406) |
| 6-481-18B | 1250 | 8 (203) | 8 (203) | 104 (2642) | HB + 16 (HB + 406) |
| 8-481-12 | 1250 | 10 (254) | 8 (203) | 95 (2413) | HB + 16 (HB + 406) |
| 8-481-21 | 1250 | 10 (254) | 8 (203) | 99 (2515) | HB + 16 (HB + 406) |
| 5-491-14A | 1250 | 8 (203) | 8 (203) | 101 (2565) | HB + 16 (HB + 406) |
| 5-491-18A | 1250 | 8 (203) | 8 (203) | 104 (2642) | HB + 16 (HB + 406) |
| 6-481-20 | 1500 | 8 (203) | 8 (203) | 104 (2642) | HB + 16 (HB + 406) |
| 6-481-15 | 1500 | 8 (203) | 8 (203) | 101 (2565) | HB + 16 (HB + 406) |
| 6-481-18B | 1500 | 8 (203) | 8 (203) | 104 (2642) | HB + 16 (HB + 406) |
| 8-481-12 | 1500 | 10 (254) | 8 (203) | 95 (2413) | HB + 16 (HB + 406) |
| 8-481-21 | 1500 | 10 (254) | 8 (203) | 99 (2515) | HB + 16 (HB + 406) |
| 6-492-10 | 1500 | 10 (254) | 8 (203) | 99 (2515) | HB + 16 (HB + 406) |
| 8-481-21 | 2000 | 10 (254) | 10 (254) | 117 (2972) | HB + 16 (HB + 406) |
| 6-481-15B | 2000 | 10 (254) | 10 (254) | 115 (2921) | HB + 16 (HB + 406) |
| 6-481-18C | 2000 | 10 (254) | 10 (254) | 118 (2997) | HB + 16 (HB + 406) |
| 6-481-20 | 2000 | 10 (254) | 10 (254) | 118 (2997) | HB + 16 (HB + 406) |
| 8-481-17B | 2000 | 10 (254) | 10 (254) | 113 (2870) | HB + 16 (HB + 406) |
| 6-491-19A | 2000 | 10 (254) | 10 (254) | 120 (3048) | HB + 16 (HB + 406) |
| 8-492-15 | 2000 | 10 (254) | 10 (254) | 110 (2794) | HB + 16 (HB + 406) |
| 8-481-21A | 2500 | 10 (254) | 10 (254) | 117 (2972) | HB + 16 (HB + 406) |
| 8-481-17B | 2500 | 10 (254) | 10 (254) | 113 (2870) | HB + 16 (HB + 406) |
| 8-491-14A | 2500 | 10 (254) | 10 (254) | 124 (3150) | HB + 16 (HB + 406) |
| 8-491-18A | 2500 | 10 (254) | 10 (254) | 124 (3150) | HB + 16 (HB + 406) |
| 10-481-18 | 3000 | 12 (305) | 12 (305) | 125 (3175) | HB + 18 (HB + 457) |
| 8-491-14A | 3000 | 12 (305) | 12 (305) | 124 (3150) | HB + 18 (HB + 457) |
| 8-491-18A | 3000 | 12 (305) | 12 (305) | 124 (3150) | HB + 18 (HB + 457) |
| 10-492-18 | 3000 | 12 (305) | 12 (305) | 124 (3150) | HB + 18 (HB + 457) |
| 10-481-18 | 3500 | 12 (305) | 12 (305) | 125 (3175) | HB + 18 (HB + 457) |
| 10-492-18 | 3500 | 12 (305) | 12 (305) | 124 (3150) | HB + 18 (HB + 457) |
| 10-481-18 | 4000 | 14 (356) | 12 (305) | 136 (3454) | HB + 18 (HB + 457) |
| 10-491-20 | 4000 | 14 (356) | 12 (305) | 146 (3708) | HB + 18 (HB + 457) |
| 10-491-20 | 4500 | 16 (406) | 14 (356) | 144 (3658) | HB + 18 (HB + 457) |
| 10-491-20 | 5000 | 16 (406) | 14 (356) | 144 (3658) | HB + 18 (HB + 457) |

NOTES

1. Refer to Section 912 & 913 for "HB" dimensions of required pump/driver combination.
2. All System dimensions are in inches (mm) and may vary ± 6 inches (152).
3. Dimensions for reference only. Refer to factory for job specific drawings.

PACKAGED FIRE PUMP SYSTEM

DIMENSIONS FOR DRAWING EFPS4

| PUMP MODEL | GPM | SYSTEM SUCTION DIAMETER | SYSTEM DISCHARGE DIAMETER | SYSTEM LENGTH | SYSTEM WIDTH |
|------------|------|-------------------------|---------------------------|---------------|--------------------|
| 4-481-11C | 750 | 6 (152) | 6 (152) | 105 (2667) | HB + 16 (HB + 406) |
| 4-481-11A | 750 | 6 (152) | 6 (152) | 105 (2667) | HB + 16 (HB + 406) |
| 4-481-15 | 750 | 6 (152) | 6 (152) | 108 (2743) | HB + 16 (HB + 406) |
| 5-481-15 | 750 | 6 (152) | 6 (152) | 100 (2540) | HB + 16 (HB + 406) |
| 4-491-11A | 750 | 6 (152) | 6 (152) | 97 (2464) | HB + 16 (HB + 406) |
| 4-491-11C | 750 | 6 (152) | 6 (152) | 97 (2464) | HB + 16 (HB + 406) |
| 4-491-14C | 750 | 6 (152) | 6 (152) | 100 (2540) | HB + 16 (HB + 406) |
| 5-491-18A | 750 | 6 (152) | 6 (152) | 117 (2972) | HB + 16 (HB + 406) |
| 6-491-12A | 750 | 6 (152) | 6 (152) | 97 (2464) | HB + 16 (HB + 406) |
| 4-492-18 | 750 | 6 (152) | 6 (152) | 109 (2769) | HB + 16 (HB + 406) |
| 5-481-11B | 1000 | 8 (203) | 6 (152) | 110 (2794) | HB + 16 (HB + 406) |
| 5-481-11C | 1000 | 8 (203) | 6 (152) | 110 (2794) | HB + 16 (HB + 406) |
| 5-481-15 | 1000 | 8 (203) | 6 (152) | 114 (2896) | HB + 16 (HB + 406) |
| 5-481-17 | 1000 | 8 (203) | 6 (152) | 115 (2921) | HB + 16 (HB + 406) |
| 6-481-11 | 1000 | 8 (203) | 6 (152) | 92 (2337) | HB + 16 (HB + 406) |
| 5-491-18A | 1000 | 8 (203) | 6 (152) | 109 (2769) | HB + 16 (HB + 406) |
| 5-492-18 | 1000 | 8 (203) | 6 (152) | 114 (2896) | HB + 16 (HB + 406) |
| 6-481-20 | 1250 | 8 (203) | 8 (203) | 114 (2896) | HB + 16 (HB + 406) |
| 6-481-15 | 1250 | 8 (203) | 8 (203) | 111 (2819) | HB + 16 (HB + 406) |
| 6-481-18B | 1250 | 8 (203) | 8 (203) | 114 (2896) | HB + 16 (HB + 406) |
| 8-481-12 | 1250 | 10 (254) | 8 (203) | 111 (2819) | HB + 16 (HB + 406) |
| 8-481-21 | 1250 | 10 (254) | 8 (203) | 115 (2921) | HB + 16 (HB + 406) |
| 5-491-14A | 1250 | 8 (203) | 8 (203) | 111 (2819) | HB + 16 (HB + 406) |
| 5-491-18A | 1250 | 8 (203) | 8 (203) | 114 (2896) | HB + 16 (HB + 406) |
| 6-481-20 | 1500 | 8 (203) | 8 (203) | 114 (2896) | HB + 16 (HB + 406) |
| 6-481-15 | 1500 | 8 (203) | 8 (203) | 111 (2819) | HB + 16 (HB + 406) |
| 6-481-18B | 1500 | 8 (203) | 8 (203) | 114 (2896) | HB + 16 (HB + 406) |
| 8-481-12 | 1500 | 10 (254) | 8 (203) | 113 (2870) | HB + 16 (HB + 406) |
| 8-481-21 | 1500 | 10 (254) | 8 (203) | 117 (2972) | HB + 16 (HB + 406) |
| 6-492-10 | 1500 | 10 (254) | 8 (203) | 113 (2870) | HB + 16 (HB + 406) |
| 8-481-21 | 2000 | 10 (254) | 10 (254) | 135 (3429) | HB + 16 (HB + 406) |
| 6-481-15B | 2000 | 10 (254) | 10 (254) | 139 (3531) | HB + 16 (HB + 406) |
| 6-481-18C | 2000 | 10 (254) | 10 (254) | 142 (3607) | HB + 16 (HB + 406) |
| 6-481-20 | 2000 | 10 (254) | 10 (254) | 142 (3607) | HB + 16 (HB + 406) |
| 8-481-17B | 2000 | 10 (254) | 10 (254) | 131 (3327) | HB + 16 (HB + 406) |
| 6-491-19A | 2000 | 10 (254) | 10 (254) | 132 (3353) | HB + 16 (HB + 406) |
| 8-492-15 | 2000 | 10 (254) | 10 (254) | 126 (3200) | HB + 16 (HB + 406) |
| 8-481-21A | 2500 | 10 (254) | 10 (254) | 135 (3429) | HB + 16 (HB + 406) |
| 8-481-17B | 2500 | 10 (254) | 10 (254) | 131 (3327) | HB + 16 (HB + 406) |
| 8-491-14A | 2500 | 10 (254) | 10 (254) | 144 (3658) | HB + 16 (HB + 406) |
| 8-491-18A | 2500 | 10 (254) | 10 (254) | 144 (3658) | HB + 16 (HB + 406) |
| 10-481-18 | 3000 | 12 (305) | 12 (305) | 145 (3683) | HB + 18 (HB + 457) |
| 8-491-14A | 3000 | 12 (305) | 12 (305) | 138 (3505) | HB + 18 (HB + 457) |
| 8-491-18A | 3000 | 12 (305) | 12 (305) | 138 (3505) | HB + 18 (HB + 457) |
| 10-492-18 | 3000 | 12 (305) | 12 (305) | 142 (3607) | HB + 18 (HB + 457) |
| 10-481-18 | 3500 | 12 (305) | 12 (305) | 145 (3683) | HB + 18 (HB + 457) |
| 10-492-18 | 3500 | 12 (305) | 12 (305) | 142 (3607) | HB + 18 (HB + 457) |
| 10-481-18 | 4000 | 14 (356) | 12 (305) | 166 (4216) | HB + 18 (HB + 457) |
| 10-491-20 | 4000 | 14 (356) | 12 (305) | 172 (4369) | HB + 18 (HB + 457) |
| 10-491-20 | 4500 | 16 (406) | 14 (356) | 164 (4166) | HB + 18 (HB + 457) |
| 10-491-20 | 5000 | 16 (406) | 14 (356) | 164 (4166) | HB + 18 (HB + 457) |

NOTES

1. Refer to Section 912 & 913 for "HB" dimensions of required pump/driver combination.
2. All System dimensions are in inches (mm) and may vary ±6 inches (152).
3. Dimensions for reference only. Refer to factory for job specific drawings.

PACKAGED FIRE PUMP SYSTEM

DIMENSIONS FOR DRAWING EFPS5

Section 918 Page 205

Date AUGUST 2000

| PUMP MODEL | GPM | SYSTEM SUCTION DIAMETER | SYSTEM DISCHARGE DIAMETER | SYSTEM LENGTH | SYSTEM WIDTH |
|------------|------|-------------------------|---------------------------|---------------|--------------------|
| 4-481-11C | 750 | 6 (152) | 6 (152) | 109 (2769) | HB + 16 (HB + 406) |
| 4-481-11A | 750 | 6 (152) | 6 (152) | 109 (2769) | HB + 16 (HB + 406) |
| 4-481-15 | 750 | 6 (152) | 6 (152) | 112 (2845) | HB + 16 (HB + 406) |
| 5-481-15 | 750 | 6 (152) | 6 (152) | 104 (2642) | HB + 16 (HB + 406) |
| 4-491-11A | 750 | 6 (152) | 6 (152) | 101 (2565) | HB + 16 (HB + 406) |
| 4-491-11C | 750 | 6 (152) | 6 (152) | 101 (2565) | HB + 16 (HB + 406) |
| 4-491-14C | 750 | 6 (152) | 6 (152) | 104 (2642) | HB + 16 (HB + 406) |
| 5-491-18A | 750 | 6 (152) | 6 (152) | 121 (3073) | HB + 16 (HB + 406) |
| 6-491-12A | 750 | 6 (152) | 6 (152) | 101 (2565) | HB + 16 (HB + 406) |
| 4-492-18 | 750 | 6 (152) | 6 (152) | 113 (2870) | HB + 16 (HB + 406) |
| 5-481-11B | 1000 | 8 (203) | 6 (152) | 114 (2896) | HB + 16 (HB + 406) |
| 5-481-11C | 1000 | 8 (203) | 6 (152) | 114 (2896) | HB + 16 (HB + 406) |
| 5-481-15 | 1000 | 8 (203) | 6 (152) | 118 (2997) | HB + 16 (HB + 406) |
| 5-481-17 | 1000 | 8 (203) | 6 (152) | 119 (3023) | HB + 16 (HB + 406) |
| 6-481-11 | 1000 | 8 (203) | 6 (152) | 96 (2438) | HB + 16 (HB + 406) |
| 5-491-18A | 1000 | 8 (203) | 6 (152) | 113 (2870) | HB + 16 (HB + 406) |
| 5-492-18 | 1000 | 8 (203) | 6 (152) | 118 (2997) | HB + 16 (HB + 406) |
| 6-481-20 | 1250 | 8 (203) | 8 (203) | 120 (3048) | HB + 16 (HB + 406) |
| 6-481-15 | 1250 | 8 (203) | 8 (203) | 117 (2972) | HB + 16 (HB + 406) |
| 6-481-18B | 1250 | 8 (203) | 8 (203) | 120 (3048) | HB + 16 (HB + 406) |
| 8-481-12 | 1250 | 10 (254) | 8 (203) | 115 (2921) | HB + 16 (HB + 406) |
| 8-481-21 | 1250 | 10 (254) | 8 (203) | 119 (3023) | HB + 16 (HB + 406) |
| 5-491-14A | 1250 | 8 (203) | 8 (203) | 117 (2972) | HB + 16 (HB + 406) |
| 5-491-18A | 1250 | 8 (203) | 8 (203) | 120 (3048) | HB + 16 (HB + 406) |
| 6-481-20 | 1500 | 8 (203) | 8 (203) | 120 (3048) | HB + 16 (HB + 406) |
| 6-481-15 | 1500 | 8 (203) | 8 (203) | 117 (2972) | HB + 16 (HB + 406) |
| 6-481-18B | 1500 | 8 (203) | 8 (203) | 120 (3048) | HB + 16 (HB + 406) |
| 8-481-12 | 1500 | 10 (254) | 8 (203) | 115 (2921) | HB + 16 (HB + 406) |
| 8-481-21 | 1500 | 10 (254) | 8 (203) | 119 (3023) | HB + 16 (HB + 406) |
| 6-492-10 | 1500 | 10 (254) | 8 (203) | 119 (3023) | HB + 16 (HB + 406) |
| 8-481-21 | 2000 | 10 (254) | 10 (254) | 141 (3581) | HB + 16 (HB + 406) |
| 6-481-15B | 2000 | 10 (254) | 10 (254) | 145 (3683) | HB + 16 (HB + 406) |
| 6-481-18C | 2000 | 10 (254) | 10 (254) | 148 (3759) | HB + 16 (HB + 406) |
| 6-481-20 | 2000 | 10 (254) | 10 (254) | 148 (3759) | HB + 16 (HB + 406) |
| 8-481-17B | 2000 | 10 (254) | 10 (254) | 137 (3480) | HB + 16 (HB + 406) |
| 6-491-19A | 2000 | 10 (254) | 10 (254) | 142 (3607) | HB + 16 (HB + 406) |
| 8-492-15 | 2000 | 10 (254) | 10 (254) | 136 (3454) | HB + 16 (HB + 406) |
| 8-481-21A | 2500 | 10 (254) | 10 (254) | 141 (3581) | HB + 16 (HB + 406) |
| 8-481-17B | 2500 | 10 (254) | 10 (254) | 137 (3480) | HB + 16 (HB + 406) |
| 8-491-14A | 2500 | 10 (254) | 10 (254) | 141 (3581) | HB + 16 (HB + 406) |
| 8-491-18A | 2500 | 10 (254) | 10 (254) | 141 (3581) | HB + 16 (HB + 406) |
| 10-481-18 | 3000 | 12 (305) | 12 (305) | 153 (3886) | HB + 18 (HB + 457) |
| 8-491-14A | 3000 | 12 (305) | 12 (305) | 150 (3810) | HB + 18 (HB + 457) |
| 8-491-18A | 3000 | 12 (305) | 12 (305) | 150 (3810) | HB + 18 (HB + 457) |
| 10-492-18 | 3000 | 12 (305) | 12 (305) | 154 (3912) | HB + 18 (HB + 457) |
| 10-481-18 | 3500 | 12 (305) | 12 (305) | 153 (3886) | HB + 18 (HB + 457) |
| 10-492-18 | 3500 | 12 (305) | 12 (305) | 154 (3912) | HB + 18 (HB + 457) |
| 10-481-18 | 4000 | 14 (356) | 12 (305) | 174 (4420) | HB + 18 (HB + 457) |
| 10-491-20 | 4000 | 14 (356) | 12 (305) | 167 (4242) | HB + 18 (HB + 457) |
| 10-491-20 | 4500 | 16 (406) | 14 (356) | 180 (4572) | HB + 18 (HB + 457) |
| 10-491-20 | 5000 | 16 (406) | 14 (356) | 180 (4572) | HB + 18 (HB + 457) |

NOTES

1. Refer to Section 912 & 913 for "HB" dimensions of required pump/driver combination.
2. All System dimensions are in inches (mm) and may vary ± 6 inches (152).
3. Dimensions for reference only. Refer to factory for job specific drawings.

■ PACKAGED FIRE PUMP SYSTEM
DIMENSIONS FOR DRAWING EFPS6

| PUMP MODEL | GPM | SYSTEM SUCTION DIAMETER | SYSTEM DISCHARGE DIAMETER | SYSTEM LENGTH | SYSTEM WIDTH |
|------------|------|-------------------------|---------------------------|---------------|--------------------|
| 4-481-11C | 750 | 6 (152) | 6 (152) | 109 (2769) | HB + 16 (HB + 406) |
| 4-481-11A | 750 | 6 (152) | 6 (152) | 109 (2769) | HB + 16 (HB + 406) |
| 4-481-15 | 750 | 6 (152) | 6 (152) | 112 (2845) | HB + 16 (HB + 406) |
| 5-481-15 | 750 | 6 (152) | 6 (152) | 104 (2642) | HB + 16 (HB + 406) |
| 4-491-11A | 750 | 6 (152) | 6 (152) | 117 (2972) | HB + 16 (HB + 406) |
| 4-491-11C | 750 | 6 (152) | 6 (152) | 117 (2972) | HB + 16 (HB + 406) |
| 4-491-14C | 750 | 6 (152) | 6 (152) | 120 (3048) | HB + 16 (HB + 406) |
| 5-491-18A | 750 | 6 (152) | 6 (152) | 127 (3226) | HB + 16 (HB + 406) |
| 6-491-12A | 750 | 6 (152) | 6 (152) | 117 (2972) | HB + 16 (HB + 406) |
| 4-492-18 | 750 | 6 (152) | 6 (152) | 129 (3277) | HB + 16 (HB + 406) |
| 5-481-11B | 1000 | 8 (203) | 6 (152) | 114 (2896) | HB + 16 (HB + 406) |
| 5-481-11C | 1000 | 8 (203) | 6 (152) | 114 (2896) | HB + 16 (HB + 406) |
| 5-481-15 | 1000 | 8 (203) | 6 (152) | 118 (2997) | HB + 16 (HB + 406) |
| 5-481-17 | 1000 | 8 (203) | 6 (152) | 119 (3023) | HB + 16 (HB + 406) |
| 6-481-11 | 1000 | 8 (203) | 6 (152) | 96 (2438) | HB + 16 (HB + 406) |
| 5-491-18A | 1000 | 8 (203) | 6 (152) | 131 (3327) | HB + 16 (HB + 406) |
| 5-492-18 | 1000 | 8 (203) | 6 (152) | 136 (3454) | HB + 16 (HB + 406) |
| 6-481-20 | 1250 | 8 (203) | 8 (203) | 120 (3048) | HB + 16 (HB + 406) |
| 6-481-15 | 1250 | 8 (203) | 8 (203) | 117 (2972) | HB + 16 (HB + 406) |
| 6-481-18B | 1250 | 8 (203) | 8 (203) | 120 (3048) | HB + 16 (HB + 406) |
| 8-481-12 | 1250 | 10 (254) | 8 (203) | 115 (2921) | HB + 16 (HB + 406) |
| 8-481-21 | 1250 | 10 (254) | 8 (203) | 119 (3023) | HB + 16 (HB + 406) |
| 5-491-14A | 1250 | 8 (203) | 8 (203) | 135 (3429) | HB + 16 (HB + 406) |
| 5-491-18A | 1250 | 8 (203) | 8 (203) | 138 (3505) | HB + 16 (HB + 406) |
| 6-481-20 | 1500 | 8 (203) | 8 (203) | 120 (3048) | HB + 16 (HB + 406) |
| 6-481-15 | 1500 | 8 (203) | 8 (203) | 117 (2972) | HB + 16 (HB + 406) |
| 6-481-18B | 1500 | 8 (203) | 8 (203) | 120 (3048) | HB + 16 (HB + 406) |
| 8-481-12 | 1500 | 10 (254) | 8 (203) | 115 (2921) | HB + 16 (HB + 406) |
| 8-481-21 | 1500 | 10 (254) | 8 (203) | 119 (3023) | HB + 16 (HB + 406) |
| 6-492-10 | 1500 | 10 (254) | 8 (203) | 141 (3581) | HB + 16 (HB + 406) |
| 8-481-21 | 2000 | 10 (254) | 10 (254) | 141 (3581) | HB + 16 (HB + 406) |
| 6-481-15B | 2000 | 10 (254) | 10 (254) | 145 (3683) | HB + 16 (HB + 406) |
| 6-481-18C | 2000 | 10 (254) | 10 (254) | 148 (3759) | HB + 16 (HB + 406) |
| 6-481-20 | 2000 | 10 (254) | 10 (254) | 148 (3759) | HB + 16 (HB + 406) |
| 8-481-17B | 2000 | 10 (254) | 10 (254) | 137 (3480) | HB + 16 (HB + 406) |
| 6-491-19A | 2000 | 10 (254) | 10 (254) | 164 (4166) | HB + 16 (HB + 406) |
| 8-492-15 | 2000 | 10 (254) | 10 (254) | 158 (4013) | HB + 16 (HB + 406) |
| 8-481-21A | 2500 | 10 (254) | 10 (254) | 141 (3581) | HB + 16 (HB + 406) |
| 8-481-17B | 2500 | 10 (254) | 10 (254) | 137 (3480) | HB + 16 (HB + 406) |
| 8-491-14A | 2500 | 10 (254) | 10 (254) | 163 (4140) | HB + 16 (HB + 406) |
| 8-491-18A | 2500 | 10 (254) | 10 (254) | 163 (4140) | HB + 16 (HB + 406) |
| 10-492-18 | 3000 | 12 (305) | 12 (305) | 178 (4521) | HB + 18 (HB + 457) |
| 10-481-18 | 3000 | 12 (305) | 12 (305) | 153 (3886) | HB + 18 (HB + 457) |
| 8-491-14A | 3000 | 12 (305) | 12 (305) | 174 (4420) | HB + 18 (HB + 457) |
| 8-491-18A | 3000 | 12 (305) | 12 (305) | 174 (4420) | HB + 18 (HB + 457) |
| 10-481-18 | 3500 | 12 (305) | 12 (305) | 153 (3886) | HB + 18 (HB + 457) |
| 10-492-18 | 3500 | 12 (305) | 12 (305) | 178 (4521) | HB + 18 (HB + 457) |
| 10-481-18 | 4000 | 14 (356) | 12 (305) | 174 (4420) | HB + 18 (HB + 457) |
| 10-491-20 | 4000 | 14 (356) | 12 (305) | 195 (4953) | HB + 18 (HB + 457) |
| 10-491-20 | 4500 | 16 (406) | 14 (356) | 210 (5334) | HB + 18 (HB + 457) |
| 10-491-20 | 5000 | 16 (406) | 14 (356) | 210 (5334) | HB + 18 (HB + 457) |

NOTES

1. Refer to Section 912 & 913 for "HB" dimensions of required pump/driver combination.
2. All System dimensions are in inches (mm) and may vary ± 6 inches (152).
3. Dimensions for reference only. Refer to factory specific drawings.

PACKAGED FIRE PUMP SYSTEM
DIMENSIONS FOR DRAWING DFPS1

Section **918** Page **211**

Date **AUGUST 2000**

| PUMP MODEL | GPM | SYSTEM SUCTION DIAMETER | SYSTEM DISCHARGE DIAMETER | SYSTEM LENGTH | SYSTEM WIDTH |
|------------|------|-------------------------|---------------------------|---------------|--------------|
| 4-481-11C | 750 | 6 (152) | 6 (152) | 105 (2667) | 109 (2769) |
| 4-481-11A | 750 | 6 (152) | 6 (152) | 105 (2667) | 109 (2769) |
| 4-481-15 | 750 | 6 (152) | 6 (152) | 108 (2743) | 109 (2769) |
| 5-481-15 | 750 | 6 (152) | 6 (152) | 111 (2819) | 112 (2845) |
| 4-491-11A | 750 | 6 (152) | 6 (152) | 107 (2718) | 113 (2870) |
| 4-491-11C | 750 | 6 (152) | 6 (152) | 107 (2718) | 113 (2870) |
| 4-491-14C | 750 | 6 (152) | 6 (152) | 110 (2794) | 115 (2921) |
| 5-491-18A | 750 | 6 (152) | 6 (152) | 115 (2921) | 116 (2946) |
| 6-491-12A | 750 | 6 (152) | 6 (152) | 107 (2718) | 113 (2870) |
| 4-492-18 | 750 | 6 (152) | 6 (152) | 109 (2769) | 116 (2946) |
| 5-481-11B | 1000 | 8 (203) | 6 (152) | 107 (2718) | 112 (2845) |
| 5-481-11C | 1000 | 8 (203) | 6 (152) | 107 (2718) | 112 (2845) |
| 5-481-15 | 1000 | 8 (203) | 6 (152) | 111 (2819) | 112 (2845) |
| 5-481-17 | 1000 | 8 (203) | 6 (152) | 111 (2819) | 112 (2845) |
| 6-481-11 | 1000 | 8 (203) | 6 (152) | 99 (2515) | 112 (2845) |
| 5-491-18A | 1000 | 8 (203) | 6 (152) | 117 (2972) | 116 (2946) |
| 5-492-18 | 1000 | 8 (203) | 6 (152) | 112 (2845) | 120 (3048) |
| 6-481-20 | 1250 | 8 (203) | 8 (203) | 118 (2997) | 115 (2921) |
| 6-481-15 | 1250 | 8 (203) | 8 (203) | 115 (2921) | 115 (2921) |
| 6-481-18B | 1250 | 8 (203) | 8 (203) | 118 (2997) | 115 (2921) |
| 8-481-12 | 1250 | 10 (254) | 8 (203) | 110 (2794) | 115 (2921) |
| 8-481-21 | 1250 | 10 (254) | 8 (203) | 114 (2896) | 121 (3073) |
| 5-491-14A | 1250 | 8 (203) | 8 (203) | 119 (3023) | 115 (2921) |
| 5-491-18A | 1250 | 8 (203) | 8 (203) | 122 (3099) | 116 (2946) |
| 6-481-20 | 1500 | 8 (203) | 8 (203) | 118 (2997) | 115 (2921) |
| 6-481-15 | 1500 | 8 (203) | 8 (203) | 115 (2921) | 115 (2921) |
| 6-481-18B | 1500 | 8 (203) | 8 (203) | 118 (2997) | 115 (2921) |
| 8-481-12 | 1500 | 10 (254) | 8 (203) | 110 (2794) | 115 (2921) |
| 8-481-21 | 1500 | 10 (254) | 8 (203) | 114 (2896) | 121 (3073) |
| 6-492-10 | 1500 | 10 (254) | 8 (203) | 119 (3023) | 120 (3048) |
| 8-481-21 | 2000 | 10 (254) | 10 (254) | 131 (3327) | 121 (3073) |
| 6-481-15B | 2000 | 10 (254) | 10 (254) | 123 (3124) | 115 (2921) |
| 6-481-18C | 2000 | 10 (254) | 10 (254) | 126 (3200) | 115 (2921) |
| 6-481-20 | 2000 | 10 (254) | 10 (254) | 126 (3200) | 115 (2921) |
| 8-481-17B | 2000 | 10 (254) | 10 (254) | 127 (3226) | 115 (2921) |
| 6-491-19A | 2000 | 10 (254) | 10 (254) | 134 (3404) | 122 (3099) |
| 8-492-15 | 2000 | 10 (254) | 10 (254) | 128 (3251) | 123 (3124) |
| 8-481-21A | 2500 | 10 (254) | 10 (254) | 133 (3378) | 121 (3073) |
| 8-481-17B | 2500 | 10 (254) | 10 (254) | 129 (3277) | 115 (2921) |
| 8-491-14A | 2500 | 10 (254) | 10 (254) | 132 (3353) | 120 (3048) |
| 8-491-18A | 2500 | 10 (254) | 10 (254) | 132 (3353) | 125 (3175) |
| 10-481-18 | 3000 | 12 (305) | 12 (305) | 139 (3531) | 121 (3073) |
| 8-491-14A | 3000 | 12 (305) | 12 (305) | 136 (3454) | 120 (3048) |
| 8-491-18A | 3000 | 12 (305) | 12 (305) | 136 (3454) | 125 (3175) |
| 10-492-18 | 3000 | 12 (305) | 12 (305) | 140 (3556) | 129 (3277) |
| 10-481-18 | 3500 | 12 (305) | 12 (305) | 139 (3531) | 121 (3073) |
| 10-492-18 | 3500 | 12 (305) | 12 (305) | 140 (3556) | 129 (3277) |
| 10-481-18 | 4000 | 14 (305) | 12 (305) | 142 (3607) | 121 (3073) |
| 10-491-20 | 4000 | 14 (305) | 12 (305) | 150 (3810) | 128 (3251) |
| 10-491-20 | 4500 | 16 (406) | 14 (356) | 148 (3759) | 128 (3251) |
| 10-491-20 | 5000 | 16 (406) | 14 (356) | 148 (3759) | 128 (3251) |

NOTES

1. Refer to Section 912 & 913 for "HB" dimensions of required pump/driver combination.
2. All System dimensions are in inches (mm) and may vary ± 6 inches (152).
3. Dimensions for reference only. Refer to factory for job specific drawings.
4. Dimensions shown are for 12 volt diesel batteries and single wall fuel tanks.

■ PACKAGED FIRE PUMP SYSTEM

DIMENSIONS FOR DRAWING DFPS2

| PUMP MODEL | GPM | SYSTEM SUCTION DIAMETER | SYSTEM DISCHARGE DIAMETER | SYSTEM LENGTH | SYSTEM WIDTH |
|------------|------|-------------------------|---------------------------|---------------|--------------|
| 4-481-11C | 750 | 6 (152) | 6 (152) | 115 (2921) | 109 (2769) |
| 4-481-11A | 750 | 6 (152) | 6 (152) | 115 (2921) | 109 (2769) |
| 4-481-15 | 750 | 6 (152) | 6 (152) | 118 (2997) | 109 (2769) |
| 5-481-15 | 750 | 6 (152) | 6 (152) | 121 (3073) | 112 (2845) |
| 4-491-11A | 750 | 6 (152) | 6 (152) | 117 (2972) | 113 (2870) |
| 4-491-11C | 750 | 6 (152) | 6 (152) | 117 (2972) | 113 (2870) |
| 4-491-14C | 750 | 6 (152) | 6 (152) | 120 (3048) | 115 (2921) |
| 5-491-18A | 750 | 6 (152) | 6 (152) | 125 (3175) | 116 (2946) |
| 6-491-12A | 750 | 6 (152) | 6 (152) | 117 (2972) | 113 (2870) |
| 4-492-18 | 750 | 6 (152) | 6 (152) | 119 (3023) | 116 (2946) |
| 5-481-11B | 1000 | 8 (203) | 6 (152) | 117 (2972) | 112 (2845) |
| 5-481-11C | 1000 | 8 (203) | 6 (152) | 117 (2972) | 112 (2845) |
| 5-481-15 | 1000 | 8 (203) | 6 (152) | 121 (3073) | 112 (2845) |
| 5-481-17 | 1000 | 8 (203) | 6 (152) | 121 (3073) | 112 (2845) |
| 6-481-11 | 1000 | 8 (203) | 6 (152) | 109 (2769) | 112 (2845) |
| 5-491-18A | 1000 | 8 (203) | 6 (152) | 127 (3226) | 116 (2946) |
| 5-492-18 | 1000 | 8 (203) | 6 (152) | 120 (3048) | 120 (3048) |
| 6-481-20 | 1250 | 8 (203) | 8 (203) | 132 (3353) | 115 (2921) |
| 6-481-15 | 1250 | 8 (203) | 8 (203) | 129 (3277) | 115 (2921) |
| 6-481-18B | 1250 | 8 (203) | 8 (203) | 132 (3353) | 115 (2921) |
| 8-481-12 | 1250 | 10 (254) | 8 (203) | 123 (3124) | 115 (2921) |
| 8-481-21 | 1250 | 10 (254) | 8 (203) | 128 (3251) | 121 (3073) |
| 5-491-14A | 1250 | 8 (203) | 8 (203) | 131 (3327) | 115 (2921) |
| 5-491-18A | 1250 | 8 (203) | 8 (203) | 134 (3404) | 116 (2946) |
| 6-481-20 | 1500 | 8 (203) | 8 (203) | 132 (3353) | 115 (2921) |
| 6-481-15 | 1500 | 8 (203) | 8 (203) | 129 (3277) | 115 (2921) |
| 6-481-18B | 1500 | 8 (203) | 8 (203) | 132 (3353) | 115 (2921) |
| 8-481-12 | 1500 | 10 (254) | 8 (203) | 123 (3124) | 115 (2921) |
| 8-481-21 | 1500 | 10 (254) | 8 (203) | 128 (3251) | 121 (3073) |
| 6-492-10 | 1500 | 10 (254) | 8 (203) | 127 (3226) | 120 (3048) |
| 8-481-21 | 2000 | 10 (254) | 10 (254) | 149 (3785) | 121 (3073) |
| 6-481-15B | 2000 | 10 (254) | 10 (254) | 141 (3581) | 115 (2921) |
| 6-481-18C | 2000 | 10 (254) | 10 (254) | 144 (3658) | 115 (2921) |
| 6-481-20 | 2000 | 10 (254) | 10 (254) | 144 (3658) | 115 (2921) |
| 8-481-17B | 2000 | 10 (254) | 10 (254) | 145 (3683) | 115 (2921) |
| 6-491-19A | 2000 | 10 (254) | 10 (254) | 152 (3861) | 122 (3099) |
| 8-492-15 | 2000 | 10 (254) | 10 (254) | 144 (3658) | 123 (3124) |
| 8-481-21A | 2500 | 10 (254) | 10 (254) | 149 (3785) | 121 (3073) |
| 8-481-17B | 2500 | 10 (254) | 10 (254) | 145 (3683) | 115 (2921) |
| 8-491-14A | 2500 | 10 (254) | 10 (254) | 150 (3810) | 120 (3048) |
| 8-491-18A | 2500 | 10 (254) | 10 (254) | 150 (3810) | 125 (3175) |
| 10-481-18 | 3000 | 12 (305) | 12 (305) | 157 (3988) | 121 (3073) |
| 8-491-14A | 3000 | 12 (305) | 12 (305) | 156 (3962) | 120 (3048) |
| 8-491-18A | 3000 | 12 (305) | 12 (305) | 156 (3962) | 125 (3175) |
| 10-492-18 | 3000 | 12 (305) | 12 (305) | 158 (4013) | 129 (3277) |
| 10-481-18 | 3500 | 12 (305) | 12 (305) | 157 (3988) | 121 (3073) |
| 10-492-18 | 3500 | 12 (305) | 12 (305) | 158 (4013) | 129 (3277) |
| 10-481-18 | 4000 | 14 (356) | 12 (305) | 160 (4064) | 121 (3073) |
| 10-491-20 | 4000 | 14 (356) | 12 (305) | 170 (4318) | 128 (3251) |
| 10-491-20 | 4500 | 16 (406) | 14 (356) | 176 (4470) | 128 (3251) |
| 10-491-20 | 5000 | 16 (406) | 14 (356) | 176 (4470) | 128 (3251) |

NOTES

1. Refer to Section 912 & 913 for "HB" dimensions of required pump/driver combination.
2. All System dimensions are in inches (mm) and may vary ± 6 inches (152).
3. Dimensions for reference only. Refer to factory for job specific drawings.
4. Dimensions shown are for 12 volt diesel batteries and single wall fuel tanks.

PACKAGED FIRE PUMP SYSTEM
DIMENSIONS FOR DRAWING DFPS3

Section **918** Page **213**

Date **AUGUST 2000**

| PUMP MODEL | GPM | SYSTEM SUCTION DIAMETER | SYSTEM DISCHARGE DIAMETER | SYSTEM LENGTH | SYSTEM WIDTH |
|------------|------|-------------------------|---------------------------|---------------|--------------|
| 4-481-11C | 750 | 6 (152) | 6 (152) | 115 (2921) | 109 (2769) |
| 4-481-11A | 750 | 6 (152) | 6 (152) | 115 (2921) | 109 (2769) |
| 4-481-15 | 750 | 6 (152) | 6 (152) | 118 (2997) | 109 (2769) |
| 5-481-15 | 750 | 6 (152) | 6 (152) | 121 (3073) | 112 (2845) |
| 4-491-11A | 750 | 6 (152) | 6 (152) | 117 (2972) | 123 (3124) |
| 4-491-11C | 750 | 6 (152) | 6 (152) | 117 (2972) | 123 (3124) |
| 4-491-14C | 750 | 6 (152) | 6 (152) | 120 (3048) | 115 (2921) |
| 5-491-18A | 750 | 6 (152) | 6 (152) | 125 (3175) | 116 (2946) |
| 6-491-12A | 750 | 6 (152) | 6 (152) | 117 (2972) | 123 (3124) |
| 4-492-18 | 750 | 6 (152) | 6 (152) | 119 (3023) | 116 (2946) |
| 5-481-11B | 1000 | 8 (203) | 6 (152) | 117 (2972) | 112 (2845) |
| 5-481-11C | 1000 | 8 (203) | 6 (152) | 117 (2972) | 112 (2845) |
| 5-481-15 | 1000 | 8 (203) | 6 (152) | 121 (3073) | 112 (2845) |
| 5-481-17 | 1000 | 8 (203) | 6 (152) | 121 (3073) | 112 (2845) |
| 6-481-11 | 1000 | 8 (203) | 6 (152) | 109 (2769) | 112 (2845) |
| 5-491-18A | 1000 | 8 (203) | 6 (152) | 127 (3226) | 116 (2946) |
| 5-492-18 | 1000 | 8 (203) | 6 (152) | 120 (3048) | 120 (3048) |
| 6-481-20 | 1250 | 8 (203) | 8 (203) | 132 (3353) | 115 (2921) |
| 6-481-15 | 1250 | 8 (203) | 8 (203) | 129 (3277) | 115 (2921) |
| 6-481-18B | 1250 | 8 (203) | 8 (203) | 132 (3353) | 115 (2921) |
| 8-481-12 | 1250 | 10 (254) | 8 (203) | 123 (3124) | 115 (2921) |
| 8-481-21 | 1250 | 10 (254) | 8 (203) | 128 (3251) | 121 (3073) |
| 5-491-14A | 1250 | 8 (203) | 8 (203) | 131 (3327) | 115 (2921) |
| 5-491-18A | 1250 | 8 (203) | 8 (203) | 134 (3404) | 116 (2946) |
| 6-481-20 | 1500 | 8 (203) | 8 (203) | 132 (3353) | 115 (2921) |
| 6-481-15 | 1500 | 8 (203) | 8 (203) | 129 (3277) | 115 (2921) |
| 6-481-18B | 1500 | 8 (203) | 8 (203) | 132 (3353) | 115 (2921) |
| 8-481-12 | 1500 | 10 (254) | 8 (203) | 123 (3124) | 115 (2921) |
| 8-481-21 | 1500 | 10 (254) | 8 (203) | 128 (3251) | 121 (3073) |
| 6-492-10 | 1500 | 10 (254) | 8 (203) | 127 (3226) | 120 (3048) |
| 8-481-21 | 2000 | 10 (254) | 10 (254) | 149 (3785) | 121 (3073) |
| 6-481-15B | 2000 | 10 (254) | 10 (254) | 141 (3581) | 115 (2921) |
| 6-481-18C | 2000 | 10 (254) | 10 (254) | 144 (3658) | 115 (2921) |
| 6-481-20 | 2000 | 10 (254) | 10 (254) | 144 (3658) | 115 (2921) |
| 8-481-17B | 2000 | 10 (254) | 10 (254) | 145 (3683) | 115 (2921) |
| 6-491-19A | 2000 | 10 (254) | 10 (254) | 152 (3861) | 122 (3099) |
| 8-492-15 | 2000 | 10 (254) | 10 (254) | 144 (3658) | 123 (3124) |
| 8-481-21A | 2500 | 10 (254) | 10 (254) | 149 (3785) | 121 (3073) |
| 8-481-17B | 2500 | 10 (254) | 10 (254) | 145 (3683) | 115 (2921) |
| 8-491-14A | 2500 | 10 (254) | 10 (254) | 150 (3810) | 120 (3048) |
| 8-491-18A | 2500 | 10 (254) | 10 (254) | 150 (3810) | 125 (3175) |
| 10-481-18 | 3000 | 12 (305) | 12 (305) | 157 (3988) | 121 (3073) |
| 8-491-14A | 3000 | 12 (305) | 12 (305) | 156 (3962) | 120 (3048) |
| 8-491-18A | 3000 | 12 (305) | 12 (305) | 156 (3962) | 125 (3175) |
| 10-492-18 | 3000 | 12 (305) | 12 (305) | 158 (4013) | 129 (3277) |
| 10-481-18 | 3500 | 12 (305) | 12 (305) | 157 (3988) | 121 (3073) |
| 10-492-18 | 3500 | 12 (305) | 12 (305) | 158 (4013) | 129 (3277) |
| 10-481-18 | 4000 | 14 (356) | 12 (305) | 160 (4064) | 121 (3073) |
| 10-491-20 | 4000 | 14 (356) | 12 (305) | 170 (4318) | 128 (3251) |
| 10-491-20 | 4500 | 16 (406) | 14 (356) | 176 (4470) | 128 (3251) |
| 10-491-20 | 5000 | 16 (406) | 14 (356) | 176 (4470) | 128 (3251) |

NOTES

1. Refer to Section 912 & 913 for "HB" dimensions of required pump/driver combination.
2. All System dimensions are in inches (mm) and may vary ± 6 inches (152).
3. Dimensions for reference only. Refer to factory for job specific drawings.
4. Dimensions shown are for 12 volt diesel batteries and single wall fuel tanks.

■ PACKAGED FIRE PUMP SYSTEM
DIMENSIONS FOR DRAWING DFPS4

| PUMP MODEL | GPM | SYSTEM SUCTION DIAMETER | SYSTEM DISCHARGE DIAMETER | SYSTEM LENGTH | SYSTEM WIDTH |
|------------|------|-------------------------|---------------------------|---------------|--------------|
| 4-481-11C | 750 | 6 (152) | 6 (152) | 121 (3073) | 109 (2769) |
| 4-481-11A | 750 | 6 (152) | 6 (152) | 121 (3073) | 109 (2769) |
| 4-481-15 | 750 | 6 (152) | 6 (152) | 124 (3150) | 109 (2769) |
| 5-481-15 | 750 | 6 (152) | 6 (152) | 121 (3073) | 112 (2845) |
| 4-491-11A | 750 | 6 (152) | 6 (152) | 117 (2972) | 113 (2870) |
| 4-491-11C | 750 | 6 (152) | 6 (152) | 117 (2972) | 113 (2870) |
| 4-491-14C | 750 | 6 (152) | 6 (152) | 120 (3048) | 115 (2921) |
| 5-491-18A | 750 | 6 (152) | 6 (152) | 133 (3378) | 116 (2946) |
| 6-491-12A | 750 | 6 (152) | 6 (152) | 117 (2972) | 113 (2870) |
| 4-492-18 | 750 | 6 (152) | 6 (152) | 125 (3175) | 116 (2946) |
| 5-481-11B | 1000 | 8 (203) | 6 (152) | 127 (3226) | 112 (2845) |
| 5-481-11C | 1000 | 8 (203) | 6 (152) | 127 (3226) | 112 (2845) |
| 5-481-15 | 1000 | 8 (203) | 6 (152) | 131 (3327) | 112 (2845) |
| 5-481-17 | 1000 | 8 (203) | 6 (152) | 131 (3327) | 112 (2845) |
| 6-481-11 | 1000 | 8 (203) | 6 (152) | 109 (2769) | 112 (2845) |
| 5-491-18A | 1000 | 8 (203) | 6 (152) | 127 (3226) | 116 (2946) |
| 5-492-18 | 1000 | 8 (203) | 6 (152) | 130 (3302) | 120 (3048) |
| 6-481-20 | 1250 | 8 (203) | 8 (203) | 132 (3353) | 115 (2921) |
| 6-481-15 | 1250 | 8 (203) | 8 (203) | 129 (3277) | 115 (2921) |
| 6-481-18B | 1250 | 8 (203) | 8 (203) | 132 (3353) | 115 (2921) |
| 8-481-12 | 1250 | 10 (254) | 8 (203) | 129 (3277) | 115 (2921) |
| 8-481-21 | 1250 | 10 (254) | 8 (203) | 134 (3404) | 121 (3073) |
| 5-491-14A | 1250 | 8 (203) | 8 (203) | 129 (3277) | 115 (2921) |
| 5-491-18A | 1250 | 8 (203) | 8 (203) | 132 (3353) | 116 (2946) |
| 6-481-20 | 1500 | 8 (203) | 8 (203) | 132 (3353) | 115 (2921) |
| 6-481-15 | 1500 | 8 (203) | 8 (203) | 129 (3277) | 115 (2921) |
| 6-481-18B | 1500 | 8 (203) | 8 (203) | 132 (3353) | 115 (2921) |
| 8-481-12 | 1500 | 10 (254) | 8 (203) | 131 (3327) | 115 (2921) |
| 8-481-21 | 1500 | 10 (254) | 8 (203) | 136 (3454) | 121 (3073) |
| 6-492-10 | 1500 | 10 (254) | 8 (203) | 131 (3327) | 120 (3048) |
| 8-481-21 | 2000 | 10 (254) | 10 (254) | 157 (3988) | 121 (3073) |
| 6-481-15B | 2000 | 10 (254) | 10 (254) | 161 (4089) | 115 (2921) |
| 6-481-18C | 2000 | 10 (254) | 10 (254) | 164 (4166) | 115 (2921) |
| 6-481-20 | 2000 | 10 (254) | 10 (254) | 164 (4166) | 115 (2921) |
| 8-481-17B | 2000 | 10 (254) | 10 (254) | 153 (3886) | 115 (2921) |
| 6-491-19A | 2000 | 10 (254) | 10 (254) | 154 (3912) | 122 (3099) |
| 8-492-15 | 2000 | 10 (254) | 10 (254) | 148 (3759) | 123 (3124) |
| 8-481-21A | 2500 | 10 (254) | 10 (254) | 157 (3988) | 121 (3073) |
| 8-481-17B | 2500 | 10 (254) | 10 (254) | 153 (3886) | 115 (2921) |
| 8-491-14A | 2500 | 10 (254) | 10 (254) | 166 (4216) | 120 (3048) |
| 8-491-18A | 2500 | 10 (254) | 10 (254) | 166 (4216) | 125 (3175) |
| 10-481-18 | 3000 | 12 (305) | 12 (305) | 169 (4293) | 121 (3073) |
| 8-491-14A | 3000 | 12 (305) | 12 (305) | 162 (4115) | 120 (3048) |
| 8-491-18A | 3000 | 12 (305) | 12 (305) | 162 (4115) | 125 (3175) |
| 10-492-18 | 3000 | 12 (305) | 12 (305) | 166 (4216) | 129 (3277) |
| 10-481-18 | 3500 | 12 (305) | 12 (305) | 169 (4293) | 121 (3073) |
| 10-492-18 | 3500 | 12 (305) | 12 (305) | 166 (4216) | 129 (3277) |
| 10-481-18 | 4000 | 14 (356) | 12 (305) | 190 (4826) | 121 (3073) |
| 10-491-20 | 4000 | 14 (356) | 12 (305) | 196 (4978) | 128 (3251) |
| 10-491-20 | 4500 | 16 (406) | 14 (356) | 192 (4877) | 128 (3251) |
| 10-491-20 | 5000 | 16 (406) | 14 (356) | 192 (4877) | 128 (3251) |

NOTES

- Refer to Section 912 & 913 for "HB" dimensions of required pump/driver combination.
- All System dimensions are in inches (mm) and may vary ± 6 inches (152).
- Dimensions for reference only. Refer to factory for job specific drawings.
- Dimensions shown are for 12 volt diesel batteries and single wall fuel tanks.

PACKAGED FIRE PUMP SYSTEM

DIMENSIONS FOR DRAWING DFPS5

Section 918 Page 215

Date AUGUST 2000

| PUMP MODEL | GPM | SYSTEM SUCTION DIAMETER | SYSTEM DISCHARGE DIAMETER | SYSTEM LENGTH | SYSTEM WIDTH |
|------------|------|-------------------------|---------------------------|---------------|--------------|
| 4-481-11C | 750 | 6 (152) | 6 (152) | 125 (3175) | 109 (2769) |
| 4-481-11A | 750 | 6 (152) | 6 (152) | 125 (3175) | 109 (2769) |
| 4-481-15 | 750 | 6 (152) | 6 (152) | 128 (3251) | 109 (2769) |
| 5-481-15 | 750 | 6 (152) | 6 (152) | 131 (3327) | 112 (2845) |
| 4-491-11A | 750 | 6 (152) | 6 (152) | 127 (3226) | 113 (2870) |
| 4-491-11C | 750 | 6 (152) | 6 (152) | 127 (3226) | 113 (2870) |
| 4-491-14C | 750 | 6 (152) | 6 (152) | 130 (3302) | 115 (2921) |
| 5-491-18A | 750 | 6 (152) | 6 (152) | 137 (3480) | 116 (2946) |
| 6-491-12A | 750 | 6 (152) | 6 (152) | 127 (3226) | 113 (2870) |
| 4-492-18 | 750 | 6 (152) | 6 (152) | 129 (3277) | 116 (2946) |
| 5-481-11B | 1000 | 8 (203) | 6 (152) | 131 (3327) | 112 (2845) |
| 5-481-11C | 1000 | 8 (203) | 6 (152) | 131 (3327) | 112 (2845) |
| 5-481-15 | 1000 | 8 (203) | 6 (152) | 135 (3429) | 112 (2845) |
| 5-481-17 | 1000 | 8 (203) | 6 (152) | 135 (3429) | 112 (2845) |
| 6-481-11 | 1000 | 8 (203) | 6 (152) | 119 (3023) | 112 (2845) |
| 5-491-18A | 1000 | 8 (203) | 6 (152) | 137 (3480) | 116 (2946) |
| 5-492-18 | 1000 | 8 (203) | 6 (152) | 134 (3404) | 120 (3048) |
| 6-481-20 | 1250 | 8 (203) | 8 (203) | 144 (3658) | 115 (2921) |
| 6-481-15 | 1250 | 8 (203) | 8 (203) | 141 (3581) | 115 (2921) |
| 6-481-18B | 1250 | 8 (203) | 8 (203) | 144 (3658) | 115 (2921) |
| 8-481-12 | 1250 | 10 (254) | 8 (203) | 133 (3378) | 115 (2921) |
| 8-481-21 | 1250 | 10 (254) | 8 (203) | 138 (3505) | 121 (3073) |
| 5-491-14A | 1250 | 8 (203) | 8 (203) | 141 (3581) | 115 (2921) |
| 5-491-18A | 1250 | 8 (203) | 8 (203) | 144 (3658) | 116 (2946) |
| 6-481-20 | 1500 | 8 (203) | 8 (203) | 144 (3658) | 115 (2921) |
| 6-481-15 | 1500 | 8 (203) | 8 (203) | 141 (3581) | 115 (2921) |
| 6-481-18B | 1500 | 8 (203) | 8 (203) | 144 (3658) | 115 (2921) |
| 8-481-12 | 1500 | 10 (254) | 8 (203) | 133 (3378) | 115 (2921) |
| 8-481-21 | 1500 | 10 (254) | 8 (203) | 138 (3505) | 121 (3073) |
| 6-492-10 | 1500 | 10 (254) | 8 (203) | 143 (3632) | 120 (3048) |
| 8-481-21 | 2000 | 10 (254) | 10 (254) | 163 (4140) | 121 (3073) |
| 6-481-15B | 2000 | 10 (254) | 10 (254) | 167 (4242) | 115 (2921) |
| 6-481-18C | 2000 | 10 (254) | 10 (254) | 170 (4318) | 115 (2921) |
| 6-481-20 | 2000 | 10 (254) | 10 (254) | 170 (4318) | 115 (2921) |
| 8-481-17B | 2000 | 10 (254) | 10 (254) | 159 (4039) | 115 (2921) |
| 6-491-19A | 2000 | 10 (254) | 10 (254) | 164 (4166) | 122 (3099) |
| 8-492-15 | 2000 | 10 (254) | 10 (254) | 158 (4013) | 123 (3124) |
| 8-481-21A | 2500 | 10 (254) | 10 (254) | 163 (4140) | 121 (3073) |
| 8-481-17B | 2500 | 10 (254) | 10 (254) | 159 (4039) | 115 (2921) |
| 8-491-14A | 2500 | 10 (254) | 10 (254) | 176 (4470) | 120 (3048) |
| 8-491-18A | 2500 | 10 (254) | 10 (254) | 176 (4470) | 125 (3175) |
| 10-481-18 | 3000 | 12 (305) | 12 (305) | 177 (4496) | 121 (3073) |
| 8-491-14A | 3000 | 12 (305) | 12 (305) | 174 (4420) | 120 (3048) |
| 8-491-18A | 3000 | 12 (305) | 12 (305) | 174 (4420) | 125 (3175) |
| 10-492-18 | 3000 | 12 (305) | 12 (305) | 178 (4521) | 129 (3277) |
| 10-481-18 | 3500 | 12 (305) | 12 (305) | 177 (4496) | 121 (3073) |
| 10-492-18 | 3500 | 12 (305) | 12 (305) | 178 (4521) | 129 (3277) |
| 10-481-18 | 4000 | 14 (356) | 12 (305) | 198 (5029) | 121 (3073) |
| 10-491-20 | 4000 | 14 (356) | 12 (305) | 208 (5283) | 128 (3251) |
| 10-491-20 | 4500 | 16 (406) | 14 (356) | 208 (5283) | 128 (3251) |
| 10-491-20 | 5000 | 16 (406) | 14 (356) | 208 (5283) | 128 (3251) |

NOTES

1. Refer to Section 912 & 913 for "HB" dimensions of required pump/driver combination.
2. All System dimensions are in inches (mm) and may vary ± 6 inches (152).
3. Dimensions for reference only. Refer to factory for job specific drawings.
4. Dimensions shown are for 12 volt diesel batteries and single wall fuel tanks.

PACKAGED FIRE PUMP SYSTEM

DIMENSIONS FOR DRAWING DFPS6

| PUMP MODEL | GPM | SYSTEM SUCTION DIAMETER | SYSTEM DISCHARGE DIAMETER | SYSTEM LENGTH | SYSTEM WIDTH |
|------------|------|-------------------------|---------------------------|---------------|--------------|
| 4-481-11C | 750 | 6 (152) | 6 (152) | 140 (3556) | 109 (2769) |
| 4-481-11A | 750 | 6 (152) | 6 (152) | 141 (3581) | 109 (2769) |
| 4-481-15 | 750 | 6 (152) | 6 (152) | 144 (3658) | 109 (2769) |
| 5-481-15 | 750 | 6 (152) | 6 (152) | 136 (3454) | 112 (2845) |
| 4-491-11A | 750 | 6 (152) | 6 (152) | 133 (3378) | 113 (2870) |
| 4-491-11C | 750 | 6 (152) | 6 (152) | 133 (3378) | 113 (2870) |
| 4-491-14C | 750 | 6 (152) | 6 (152) | 136 (3454) | 115 (2921) |
| 5-491-18A | 750 | 6 (152) | 6 (152) | 143 (3632) | 116 (2946) |
| 6-491-12A | 750 | 6 (152) | 6 (152) | 133 (3378) | 113 (2870) |
| 4-492-18 | 750 | 6 (152) | 6 (152) | 145 (3683) | 116 (2946) |
| 5-481-11B | 1000 | 8 (203) | 6 (152) | 148 (3759) | 112 (2845) |
| 5-481-11C | 1000 | 8 (203) | 6 (152) | 148 (3759) | 112 (2845) |
| 5-481-15 | 1000 | 8 (203) | 6 (152) | 152 (3861) | 112 (2845) |
| 5-481-17 | 1000 | 8 (203) | 6 (152) | 153 (3886) | 112 (2845) |
| 6-481-11 | 1000 | 8 (203) | 6 (152) | 130 (3302) | 112 (2845) |
| 5-491-18A | 1000 | 8 (203) | 6 (152) | 147 (3734) | 116 (2946) |
| 5-492-18 | 1000 | 8 (203) | 6 (152) | 152 (3861) | 120 (3048) |
| 6-481-20 | 1250 | 8 (203) | 8 (203) | 156 (3962) | 115 (2921) |
| 6-481-15 | 1250 | 8 (203) | 8 (203) | 153 (3886) | 115 (2921) |
| 6-481-18B | 1250 | 8 (203) | 8 (203) | 156 (3962) | 115 (2921) |
| 8-481-12 | 1250 | 10 (254) | 8 (203) | 155 (3937) | 115 (2921) |
| 8-481-21 | 1250 | 10 (254) | 8 (203) | 160 (4064) | 121 (3073) |
| 5-491-14A | 1250 | 8 (203) | 8 (203) | 153 (3886) | 115 (2921) |
| 5-491-18A | 1250 | 8 (203) | 8 (203) | 156 (3962) | 116 (2946) |
| 6-481-20 | 1500 | 8 (203) | 8 (203) | 156 (3962) | 115 (2921) |
| 6-481-15 | 1500 | 8 (203) | 8 (203) | 153 (3886) | 115 (2921) |
| 6-481-18B | 1500 | 8 (203) | 8 (203) | 156 (3962) | 115 (2921) |
| 8-481-12 | 1500 | 10 (254) | 8 (203) | 155 (3937) | 115 (2921) |
| 8-481-21 | 1500 | 10 (254) | 8 (203) | 160 (4064) | 121 (3073) |
| 6-492-10 | 1500 | 10 (254) | 8 (203) | 160 (4064) | 120 (3048) |
| 8-481-21 | 2000 | 10 (254) | 10 (254) | 185 (4699) | 121 (3073) |
| 6-481-15B | 2000 | 10 (254) | 10 (254) | 189 (4801) | 115 (2921) |
| 6-481-18C | 2000 | 10 (254) | 10 (254) | 192 (4877) | 115 (2921) |
| 6-481-20 | 2000 | 10 (254) | 10 (254) | 192 (4877) | 115 (2921) |
| 8-481-17B | 2000 | 10 (254) | 10 (254) | 180 (4572) | 115 (2921) |
| 6-491-19A | 2000 | 10 (254) | 10 (254) | 186 (4724) | 122 (3099) |
| 8-492-15 | 2000 | 10 (254) | 10 (254) | 180 (4572) | 123 (3124) |
| 8-481-21A | 2500 | 10 (254) | 10 (254) | 185 (4699) | 121 (3073) |
| 8-481-17B | 2500 | 10 (254) | 10 (254) | 181 (4597) | 115 (2921) |
| 8-491-14A | 2500 | 10 (254) | 10 (254) | 185 (4699) | 120 (3048) |
| 8-491-18A | 2500 | 10 (254) | 10 (254) | 185 (4699) | 125 (3175) |
| 10-481-18 | 3000 | 12 (305) | 12 (305) | 201 (5105) | 121 (3073) |
| 8-491-14A | 3000 | 12 (305) | 12 (305) | 198 (5029) | 120 (3048) |
| 8-491-18A | 3000 | 12 (305) | 12 (305) | 198 (5029) | 125 (3175) |
| 10-492-18 | 3000 | 12 (305) | 12 (305) | 202 (5131) | 129 (3277) |
| 10-481-18 | 3500 | 12 (305) | 12 (305) | 201 (5105) | 121 (3073) |
| 10-492-18 | 3500 | 12 (305) | 12 (305) | 202 (5131) | 129 (3277) |
| 10-481-18 | 4000 | 14 (356) | 12 (305) | 226 (5740) | 121 (3073) |
| 10-491-20 | 4000 | 14 (356) | 12 (305) | 219 (5563) | 128 (3251) |
| 10-491-20 | 4500 | 16 (406) | 14 (356) | 238 (6045) | 128 (3251) |
| 10-491-20 | 5000 | 16 (406) | 14 (356) | 238 (6045) | 128 (3251) |

NOTES

1. Refer to Section 912 & 913 for "HB" dimensions of required pump/driver combination.
2. All System dimensions are in inches (mm) and may vary ± 6 inches (152).
3. Dimensions for reference only. Refer to factory for job specific drawings.
4. Dimensions shown are for 12 volt diesel batteries and single wall fuel tanks.